


# B402 - 3U VMEbus Intelligent I/O Controller



- **MC68332/20MHz**
- **1-slot VME master/slave or busless**
- **1 M-Module slot**

The B402 CPU board is a universal intelligent VMEbus master and/or slave. Being equipped with sufficient local EPROM/Flash, SRAM, RTC etc., the 32-bit CPU (MC68332) handles one local M-Module.

The B402 makes use of the 16 TPU channels ("Time Processing Units") of the RISC CPU inside the 68332. The TPU channels provide user-defined intelligent timer functions, for example for signal analysis. All TPU lines for the on-board M-Module are available as TTL signals on row C of the M-Module I/O connector. The B402 can access the VMEbus as an A24/A16/D16

master, and it can also perform slot-1 function. As a slave, the board has 2MB of genuine dual-ported RAM. Due to its bus architecture and I/O modularity the B402 is suited for a myriad of applications. Together with an M-Module it can be used as a controlling computer or can fulfill I/O tasks in a VMEbus multimaster system.

Its genuine dual-ported RAM makes the B402 also an ideal choice for use as an intelligent data acquisition system or for handling local I/O tasks.

## Technical Data

### Microcontroller

- 32-bit CPU MC68332/20MHz

### Memory

- Up to 1MB "genuine" dual-ported SRAM
- Up to 2MB EPROM (two 32-pin JEDEC sockets, also for EEPROMs or NOVRAMs)
- Up to 1MB SRAM, battery backup possible via VMEbus

### M-Module Extension

- 1 M-Module slot
- Characteristics: A08, D08, D16, INTA, INTC, TRIGI, TRIGO
- User-defined row of 60-pin connector

### Interfaces

- Serial interface via interface adapters (optional)

### VMEbus

- 3U VMEbus form factor
- A16, A24, D16
- Single-level bus arbiter/RWD-ROR bus requester
- Single-level interrupt handler/requester
- Single-level location monitor
- DTB master/slave
- Bus timer

### Miscellaneous

- Programmable hardware watchdog
- Battery-backed real-time clock
- Eight user-programmable LEDs
- One user-readable rotary coding switch
- Single 5V power supply (except M-Module)

### Electrical Specifications

- Isolation voltage: 500V DC
- Supply voltage/power consumption: +5V (4.85V..5.25V), 1A typ.
- MTBF: 38,000h @ 50°C

### Mechanical Specifications

- Dimensions: single Eurocard (100mm x 160mm)
- Weight: 140g

### Environmental Specifications

- Temperature range (operation):
  - 0..+60°C
  - Industrial temperature range on request
  - Airflow: min. 10m<sup>3</sup>/h
- Temperature range (storage): -40..+85°C
- Relative humidity range (operation): max. 95% non-condensing
- Relative humidity range (storage): max. 95% non-condensing
- Altitude: -300m to + 3,000m
- Shock: 15g/0.33ms, 6g/6ms
- Vibration: 1g/5..2,000Hz

### Safety

- PCB manufactured with a flammability rating of 94V-0 by UL recognized manufacturers


### EMC

- Tested according to EN 55022 / 1999-05 (radio disturbance) and EN 55024 / 1999-05 (immunity) with regard to CE conformity

### Software Support

- MENMON
- OS-9

### Diagram



## Related Products

### Standard Hardware

01B402-02	B402, VMEbus 3U, CPU 68332/20 MHz, 256KB global dual-ported SRAM, 1MB local SRAM, 1MB Flash, 1 M-Module slot
-----------	--

### Systems & Card Cages

Disk drives for basic systems are delivered as requested. Different rack sizes, power supplies and backplanes on request.

0700-0009	CE-conformal housing for VMEbus 3U: closed 19" rack, 4U, 9 slots, J1 backplane, power supply 230V, fan
-----------	--

### Accessories

05B402-00	Accessory B402: 1-slot front panel with flat cable for use of serial interface adapters
05M000-15	Front-panel cover for M-Module cut-outs at front panels, snap-in, 10 pcs
08SA01-00	Serial interface adapter, RS232, not optically isolated, 0..+60°C
08SA02-00	Serial interface adapter, RS422/485, half duplex, optically isolated, 0..+60°C
08SA02-01	Serial interface adapter, RS422/485, full duplex, optically isolated, 0..+60°C
08SA02-07	Serial interface adapter, RS422/485, full duplex, optically isolated, temperature range: -40..+85°C
08SA03-00	Serial interface adapter, RS232, optically isolated, 0..+60°C
08SA03-01	Serial interface adapter, RS232, optically isolated, -40..+85°C
08SA04-00	Serial interface adapter, TTY, optically isolated, 0..+60°C

For more functions realized with SA adapters, see the listing on MEN's website. You can also view our SA adapter compare chart for a quick overview of different functions. Please contact sales to make sure that these SA adapters can be used in the board configuration you are looking for.

### Software

10ABMX-07	OS-9 V.3.0: OS-9/68k + NET license
10B402-01	OS-9 V.3.0: BSP for B402 (object code, PC disk format, MEN)

For OS-9 BSP and driver support provided by MEN please refer to the ordering numbers below.

### Documentation

## Related Products

20B402-00 B402 user manual

For the most up-to-date ordering information and direct links to other data sheets and downloads, see the B402 online data sheet under [www.men.de](http://www.men.de). --> [Click here!](#)

### Germany

MEN Mikro Elektronik GmbH  
Neuwieder Straße 5-7  
90411 Nuremberg  
Phone +49-911-99 33 5-0  
Fax +49-911-99 33 5-901  
E-mail [info@men.de](mailto:info@men.de)  
[www.men.de](http://www.men.de)

### France

MEN Mikro Elektronik SA  
18, rue René Cassin  
ZA de la Châtelaine  
74240 Gaillard  
Phone +33 (0) 450-955-312  
Fax +33 (0) 450-955-211  
E-mail [info@men-france.fr](mailto:info@men-france.fr)  
[www.men-france.fr](http://www.men-france.fr)

### UK

MEN Micro Ltd  
Whitehall, 75 School Lane  
Hartford, Northwich  
Cheshire UK, CW8 1PF  
Phone +44 (0) 1477-549-185  
Fax +44 (0) 1477-549-178  
E-mail [info@menmicro.co.uk](mailto:info@menmicro.co.uk)  
[www.menmicro.co.uk](http://www.menmicro.co.uk)

### USA

MEN Micro, Inc.  
PO Box 4160  
Lago Vista, TX 78645-4160  
Phone (512) 267-8883  
Fax (512) 267-8803  
E-mail [sales@menmicro.com](mailto:sales@menmicro.com)  
[www.menmicro.com](http://www.menmicro.com)

*The date of issue stated in this data sheet refers to the Technical Data only. Changes in ordering information given herein do not affect the date of issue. All brand or product names are trademarks or registered trademarks of their respective holders.*

*Information in this document has been carefully checked and is believed to be accurate as of the date of publication; however, no responsibility is assumed for inaccuracies. MEN Mikro Elektronik accepts no liability for consequential or incidental damages arising from the use of its products and reserves the right to make changes on the products herein without notice to improve reliability, function or design. MEN Mikro Elektronik does not assume any liability arising out of the application or use of the products described in this document.*

*The products of MEN Mikro Elektronik are not suited for use in nuclear reactors and for application in medical appliances used for therapeutical purposes. Application of MEN's products in such plants is only possible after the user has precisely specified the operation environment and after MEN Mikro Elektronik has consequently adapted and released the product.*

*Copyright © 2004 MEN Mikro Elektronik GmbH. All rights reserved.*